



MODEL NO. 06.0625.LIB
Rechargeable LED Spotlight



INTRODUCTION

Congratulations on purchasing your new **SHO-ME**® Lithium-Ion LED Spotlight. Read this Instruction Manual and follow the instructions carefully before using your new spotlight.

OPERATING INSTRUCTIONS:

Operating the spotlight

Press the On/Off trigger once to use the spotlight.
Press the On/Off trigger again to turn off the spotlight.

SPECIFICATIONS:

Spotlight

LEDs: 9 - 3 watt
Battery: Lithium-Ion, 7.4V DC 2600mAh

AC Adapter

Input: AC100-240V 50/60HZ
Output Voltage: 8.4V volts DC 1A

DC Adapter

Input: 12-24 volts DC
Output Voltage: 8.4 volts DC 1A
Fuse: 3 Amp in DC Plug

SPECIFIC SAFETY INSTRUCTIONS FOR LITHIUM-ION BATTERIES

WARNING: TO REDUCE THE RISK OF FIRE, ELECTRIC SHOCK, BURST HAZARD, OR INJURY TO PERSONS OR PROPERTY:

Lithium-ion batteries are small, compact and ideal for providing long-lasting power to this unit. However, they must be used and charged properly. Improper use can result in serious injury, fire, or death.

Lithium-ion batteries can explode in the presence of a source of ignition. Do not use the product in the presence of an open flame.

Do not place this lithium-ion battery powered unit in fire or apply heat to it.

Do not subject this lithium-ion battery powered unit to strong impacts or shocks. The battery in this unit contains safety and protection devices which, if damaged, may cause the battery to generate heat, rupture or ignite.

Do not expose this lithium-ion battery powered unit to water or salt water, or allow the battery to get wet.

Avoid storing this lithium-ion battery powered unit in the basement, bathroom or other areas of the house that are or may become wet or humid or where moisture may concentrate.

Do not leave this lithium-ion battery powered unit in direct sunlight, or use or store the unit inside cars in hot weather. Doing so may cause the battery to generate heat, rupture, or ignite. Using the battery in this manner may also result in a loss of performance and a shortened life expectancy.

Never charge this unit near heat or flammable objects.

NEVER THROW WATER ON A BURNING LI-ION BATTERY! If a lithium-ion battery does catch on fire, it will burn even more violently if it comes in contact with water or even moisture in the air. A fire extinguisher must be used.

READING THE BATTERY/CHARGE STATUS LED INDICATOR

The battery and charging status LED indicator is located on the charger.

When connected to AC wall charger or DC adaptor charger :

Red: Battery Charging.

Green: Battery is in a fully charged state.

Charging/recharging using the 120 Volt AC Adapter

Make sure the spotlight is off.

Insert the barrel connector of the AC Adapter into the 12VDC Charging Port on the back of the unit. Insert the plug end into a (powered) standard North American 120 volt 60Hz outlet.

Charge until the battery/charge status LED indicator lights green.

Charging/recharging using the 12 Volt DC Adapter

Make sure the spotlight is off.

Insert the barrel tip of the 12 Volt DC Adapter into the 12VDC Charging Port on the back of the unit.

Insert the 12 volt DC plug end into the accessory outlet of your vehicle or other 12 volt DC power source.

Charge until the battery/charge status LED indicator lights green.

Notes:

When using a vehicle's 12 volt DC accessory outlet as a charging source, be aware that some vehicles require you to turn on the ignition to power the accessory outlet.